

AURORA XDLSN3 – PUSH BUTTON

A wireless IoT sensor system

ABOUT

The AURORA Push Button unit lets you detect user clicks. Possible application areas include event tracking, alarming, and data simulation in existing AURORA networks. The unit is equipped with one CR123, 1550mA battery if using LoRa or two batteries if using NarrowBand.

Connectivity

The module can be configured with LoRa, NarrowBand, SMARTMESH IP or Sigfox.

General Specifications	Min	Max	Other
Operating temperature	-20° C	50° C	
Storage temperature	-20° C	40° C	
Supply Voltage	1.6 V	3.6 V	
Battery	-	-	CR123, 1550mA
IP Level	-	-	IP 64
Dimensions ⁽¹⁾	-	-	70mm(L), 50mm(W), 30mm(D)

TEMPERATURE SENSOR	Min	Max
High Accuracy Temperature Sensor ± 0.4 °C (max)	-10°C	85°C
Power Consumption	60 μ A	150 μ A

